

## Armadillo LED - Evolution In Lighting

Tel. 0845 060 4000 Intl. +44 1371 87 69 69  
Fax. 0845 060 4001 Intl. +44 1371 87 54 37

Bigods Hall | Bigods Lane | Great Dunmow | Essex | CM6 3BE | England

email: [sales@armark.com](mailto:sales@armark.com) web: [www.armadilloLED.com](http://www.armadilloLED.com) online: @armadilloled

# IP65 LED Robust IP65 Rated LED Lighting



© 2014 Armadillo LED - Evolution In Lighting (part of Armadillo Marketing Limited est. 1996)  
All rights reserved. Reproduction in whole or in part is prohibited without the prior written consent of the copyright owner. The information presented in this document does not form part of any quotation or contract, is believed to be accurate and reliable and may be changed without notice.  
No liability will be accepted by the publisher for any consequence of its use.



## IP65 LED Lighting

Lightweight, flexible and durable polycarbonate construction makes the luminaire vandal resistant and highly impact resistant. The UV stabilized polycarbonate diffuser eliminates glare and is integrated with crystals that assist in the enhancement of even light distribution (clear lens optional). Eight closure clips securely and evenly seal the luminaire.

Long life LEDs, coupled with a high-efficiency driver, provide superior quality of illumination for extended service life. Rated to deliver LM80 performance for 50,000 hours. Stainless steel mounting hardware for wall, ceiling or suspended mounting.

Available with Barracuda 340 LED tubes or Samsung LED strip, supplied with 5 year Warranty as standard.

### Single IP65 with Barracuda 340 LED Tubes



<b>Colour Temperature</b>	4000K (Optional: 3000k, 5000K)
<b>Colour Rendering Index</b>	>80 CRI
<b>Wattage</b>	9W, 18W, 22W
<b>Lifetime</b>	>50,000 Hours
<b>IP Rating</b>	>IP65
<b>Voltage</b>	AC100-277V 50/60Hz

<b>Warranty</b>	5 Years
<b>Efficiency</b>	>100lm/w
<b>Operating Temp</b>	- 35°C ~ +85°C

IP65-2FT-SINGLE-TUBE-4K/5K-9W	IP65 WEATHERPROOF LED FITTING 4K/5K CRI>80 9W FOR BARRACUDA 340 S/S CLIPS
IP65-4FT-SINGLE-TUBE-4K/5K-18W	IP65 WEATHERPROOF LED FITTING 4K/5K CRI>80 18W FOR BARRACUDA 340 S/S CLIPS
IP65-5FT-SINGLE-TUBE-4K/5K-22W	IP65 WEATHERPROOF LED FITTING 4K/5K CRI>80 22W FOR BARRACUDA 340 S/S CLIPS

### Twin IP65 with Barracuda 340 LED Tubes



<b>Colour Temperature</b>	4000K (Optional: 3000k, 5000K)
<b>Colour Rendering Index</b>	>80 CRI
<b>Wattage</b>	18W, 36W
<b>Lifetime</b>	>50,000 Hours
<b>IP Rating</b>	IP65
<b>Voltage</b>	AC100-277V 50/60Hz

<b>Warranty</b>	5 Years
<b>Efficiency</b>	>100lm/w
<b>Operating Temp</b>	- 35°C ~ +85°C

IP65-2FT-TWIN-TUBE-4K/5K-18W	IP65 WEATHERPROOF LED FITTING 4K/5K CRI>80 18W FOR BARRACUDA 340 S/S CLIPS
IP65-4FT-TWIN-TUBE-4K/5K-36W	IP65 WEATHERPROOF LED FITTING 4K/5K CRI>80 36W FOR BARRACUDA 340 S/S CLIPS

**Single IP65 with LED Strips**



**Colour Temperature** 4000K (Optional: 3000k, 5000K)  
**Colour Rendering Index** >80 CRI  
**Wattage** 16W, 25W  
**Lifetime** >50,000 Hours  
**IP Rating** IP65  
**Voltage** AC100-277V 50/60Hz  
**Dimming** 1-10V (Optional: DALI)

**Warranty** 5 Years  
**Efficiency** >95lm/w  
**Power Supply** Meanwell  
**Power Factor** >0.95  
**Operating Temp** -30°C ~ +40°C

IP65-2FT-SINGLE-4K/5K-16W	IP65 WEATHERPROOF LED FITTING 4K/5K CRI>80 16W SAMSUNG LED S/S CLIPS MW DRIVER
IP65-4FT-SINGLE-4K/5K-25W	IP65 WEATHERPROOF LED FITTING 4K/5K CRI>80 25W SAMSUNG LED S/S CLIPS MW DRIVER
IP65-5FT-SINGLE-4K/5K-25W	IP65 WEATHERPROOF LED FITTING 4K/5K CRI>80 25W SAMSUNG LED S/S CLIPS MW DRIVER

**Twin IP65 with LED Strips**





**Colour Temperature** 4000K (Optional: 3000k, 5000K)  
**Colour Rendering Index** >80 CRI  
**Wattage** 25W, 40W, 50W, 60W  
**Lifetime** >50,000 Hours  
**IP Rating** IP65  
**Voltage** AC100-277V 50/60Hz  
**Dimming** 1-10V (Optional: DALI)

**Warranty** 5 Years  
**Efficiency** >95lm/w  
**Power Supply** Meanwell  
**Power Factor** >0.95  
**Operating Temp** -30°C ~ +40°C

IP65-2FT-TWIN-4K/5K-25W	IP65 WEATHERPROOF LED FITTING 4K/5K CRI>80 20W SAMSUNG LED S/S CLIPS MW DRIVER
IP65-4FT-TWIN-4K/5K-40W	IP65 WEATHERPROOF LED FITTING 4K/5K CRI>80 40W SAMSUNG LED S/S CLIPS MW DRIVER
IP65-4FT-TWIN-4K/5K-50W	IP65 WEATHERPROOF LED FITTING 4K/5K CRI>80 50W SAMSUNG LED S/S CLIPS MW DRIVER
IP65-4FT-TWIN-4K/5K-60W	IP65 WEATHERPROOF LED FITTING 4K/5K CRI>80 60W SAMSUNG LED S/S CLIPS MW DRIVER

40W will replace a twin 4ft. 50W will replace a twin 5ft. 60W will replace a twin 6ft.




## Safety Instructions

1. READ AND FOLLOW ALL SAFETY INSTRUCTIONS.
2. Disconnect the power supply while replacing or maintaining the product to prevent electric shocks.
3. Reconstruction or the use of accessory equipment not recommended, may cause an unsafe condition, and will void the unit's warranty.
4. Servicing of this equipment should be performed by qualified service personnel.
5. Do not mount near electric or gas heaters.
6. Do not use this equipment for other than its intended purpose.
7. SAVE THESE INSTRUCTIONS.


## Application

### 1. Product Installation




### 3. Mounting brackets installation and take-down


step1 Use screwdriver to prize open the clips  
prize up by screwdriver




step2 Take down the diffuser.




step3 Install or replace the LED Tubes.



step4 Close the diffuser, and push inward the clips by hand.




### 3 Power connection




### 4. Clips installation

Note: Leave the clips on Housing  
Clips' matching part of the housing



### 6. Mounting types

#### a) Chain mounting



#### b) Mounting brackets ceiling mounting

